Type: 45051 Single Phase Under and Over Voltage plus Time Delay

- Detects Under or Over voltage condition
- □ Monitors own supply
- **Gamma** Separate adjustment for upper level and lower level
- □ User selectable nominal voltage (24, 115 or 230V)
- **D** Time delay (from fault) with adjustable setting
- □ I x SPDT relay output
- **LED** indication for supply and relay status

• FUNCTION DIAGRAM



INSTALLATION AND SETTING

BEFORE INSTALLATION, ISOLATE THE SUPPLY.

- Connect the unit as shown in the diagram below.
- Select the correct nominal voltage using the rotary switch.
- If using the unit at 24V~ fit the link across A1 and A3.
- Set the 'over volts' adjustment to maximum and the 'under volts' adjustment to minimum.
- Set the 'delay' adjustment to minimum.
- Apply power (green '**supply on**' and red '**relay**' LED's will illuminate, the relay will energise and contacts 15 and 18 will close).

To set the unit:

- Set the 'over volts' and 'under volts' adjustments to give the required range.
- If large supply variations are anticipated, the adjustments should be set further away from the nominal.
- Set the '**delay**' adjustment as required.
- Note: The unit incorporates a 'power on delay (Td)' which operates immediately the supply is applied. The delay prevents the relay from energising if the measured voltage is above or below the set levels.

Troubleshooting.

• If the unit fails to operate as described, check the wiring, linking (24V only) and voltages present on the supply terminals.

<u>CONNECTION DIAGRAM</u>



Dims: H. 78mm W. 45mm L. 99mm

TECHNICAL SPECIFICATION Supply/Monitored 24/115/230V AC 45 - 65Hz voltage Un*: Supply variation: 85 - 115% of Un Rated impulse withstand voltage: 4kV (1.2/50µS) Power ≈ 1.5 VA @ 27.6V consumption: ≈ 9 VA @ 264V (maximum) 24, 115 or 230V selectable by rotary switch *Voltage selection: Under trip level: 87 - 110% of Un 90 - 113% of Un Over trip level: Measuring ranges: Lower Upper 21 - 26.5V AC 21.5 - 27V AC 24V· 115V: 100 - 126.5V AC 103.5 - 130V AC 230V: 200 - 253V AC 207 - 260V AC (N.B. Unit will measure average value of own supply whereas scale ranges are calibrated to RMS value) +5%Accuracy: ≈2% Hysteresis : Reaction time: τ < 200mS, worst case reaction may be up to $5 \times \tau$ 0.1 - 10S (-10/+30% on max setting) Adjustable time (N.B. t = set delay + reaction time)delay (t): On delay (Td): ≈ 2S, actual delay may be Td / 2 Ambient temp: -20 to +50°C +95% Relative humidity: SPDT relay Output: 250V AC 5A (1250VA) AC I Output rating AC 15 250V AC 3A DC I 25V DC 5A (125W) Electrical life: ≥ 150,000 ops at rated load Housing: Orange flame retardant UL94 VO $\approx 337 \,\text{g}$ On to 35mm symmetric DIN rail to Weight: Mounting option: BS5584:1978 (EN50 002, DIN 46277-3) Conforms to UL, CUL, CSA & IEC Approvals: **(**Compliant

MOUNTING DETAILS



Broyce Control Ltd., Pool Street, Wolverhampton, West Midlands WV2 4HN. England

4505 I -A2000-08-30

Telephone: +44 (0) 1902 773746 Facsimile: +44 (0) 1902 420639 Email: sales@broycecontrol.com Web: http://www.broycecontrol.com The information provided in this literature is believed to be accurate (subject to change without prior notice); however, use of such information shall be entirely at the user's own risk.